

Optical Interconnection Design Innovator

P/N: GLQE-PC101-DXX

GIGALIGHT 100G QSFP28 immersion cooling extender

Features

- ✓ Compliant QSFP MSA
- ✓ Typical insertion loss less 5dB@12.89GHz
- ✓ 100ohm differential impedance system
- ✓ 3.3V power supply
- ✓ I2C R/W function
- Status indicators with LED
- ✓ Low EMI radiation and crosstalk
- ✓ RoHS 6 compliant(lead free)

Applications

- ✓ Extend 100G/40G transceiver/AOC for liquid immersion link environment
- Protect device QSFP SMT connector
- ✓ provide I2C R/W and some status indicators with LED

Description

Gigalight can offer rich experience of immersion solution, that includes different form and speed transceivers/AOC product. Gigalight 100G QSFP28 immersion cooling extender (GLQE-PC101-DXX) is an important part of liquid immersion solution, normal QSFP form transceiver/AOC can be used for immersion environment with this product. This product include extender cage, cable, QSFP housing three parts, the cable length can be customized no more than 0.5m for extension, that can avoid the optical lens/engine/interface exposure to the liquid indirectly.



In addition, this product can provide I2C read/write, also can show the status indicators with LED for low speed electrical hardware pins. When insertion and removal frequently, this product can effectively protect the QSFP SMT connector of switch/NIC.

Liquid cooling Advantage



Figure 1. Liquid cooling advantage

As the requirement of data traffic keeping growth and the heat flux emitted by datacenter internal chips increases constantly, traditional air cooling methods are under pressure. Liquid cooling technologies removes the heat more efficiently with dielectric fluids that have high heat capacity to improve the efficiency of energy in datacenter.

Gigalight solved the lack of optical transceivers which perform reliability in immersion even liquid immersion depth up to 10m, the Liquid cooling optical series transceiver is suitable for liquid cooling server & system, this series product are compatible with fluorinated liquid and mineral oils well.

Immersion cooling extender can also be a important role in liquid immersion solution, existing normal QSFP form transceiver/AOC can be adapted for immersion indirectly.





Optical Interconnection Design Innovator

Figure 2.QSFP28 immersion cooling extender under liquid

Absolute Maximum Ratings

Parameter	Symbol	Min	Мах	Unit
Storage Temperature	Ts	-20	85	°C
Case Operating Temperature	Tc	0	70	°C
Humidity (non-condensing)	Rh	5	95	%

Recommended Operating Conditions

Parameter	Symbol	Min	Typical	Мах	Unit
Operating Case Temperature	Tc	-20		70	°C
Baud Rate per Lane	fd		25.78		GBaud/s
Humidity	Rh	5		85	%

Main Part assembly



Figure 3.QSFP28 extender main part assembly

Extender contact Pin Description

Pin	Logic	Symbol	Name/Description
1		GND	Module Ground ^{Note5}
2	CML-I	Tx2-	Transmitter inverted data input
3	CML-I	Tx2+	Transmitter non-inverted data input
4		GND	Module Ground Note5
5	CML-I	Tx4-	Transmitter inverted data input
6	CML-I	Tx4+	Transmitter non-inverted data input



www.gigalight.com

深圳市易飞扬通信技术有限公司 Shenzhen Gigalight Technology Co., Ltd.

Optical Interconnection Design Innovator

Module Ground^{Note5} GND 7 8 LVTTL-I MODSEIL Module Select^{Note6} Module Reset^{Note6} LVTTL-I 9 ResetL 10 VCCRx +3.3V Power Supply LVCMOS-I 11 SCL 2-wire Serial interface clock^{Note6} 12 LVCMOS-I/O SDA 2-wire Serial interface data^{Note6} Module Ground^{Note5} 13 GND 14 CML-O **RX3+** Receiver non-inverted data output 15 CML-O RX3-Receiver inverted data output Module Ground^{Note5} 16 GND 17 CML-O RX1+ Receiver non-inverted data output 18 CML-O **RX1-**Receiver inverted data output Module Ground^{Note5} 19 GND Module Ground^{Note5} 20 GND 21 CML-O RX2-Receiver inverted data output 22 Receiver non-inverted data output CML-O RX2+ Module Ground^{Note5} 23 GND 24 CML-O RX4-Receiver inverted data output 25 CML-O RX4+ Receiver non-inverted data output Module Ground^{Note5} 26 GND 27 ModPrsL LVTTL-O Module Present, internal pulled down to GND 28 Interrupt output, should be pulled up on host board² LVTTL-O IntL 29 VCCTx +3.3V Transmitter Power Supply 30 VCC1 +3.3V Power Supply Low Power Mode^{Note6} 31 LVTTL-I LPMode 32 GND Module Ground^{Note5} 33 CML-I Tx3+ Transmitter non-inverted data input CML-I 34 Tx3-Transmitter inverted data input 35 GND Module Ground^{Note5} Tx1+ 36 CML-I Transmitter non-inverted data input 37 CML-I Tx1-Transmitter inverted data input 38 GND Module Ground^{Note5}



Note:

- 1. Module circuit ground is isolated from module chassis ground within the module.
- 2. Open collector should be pulled up with 4.7K to 10K ohms on host board to a voltage between 3.15V and

3.6V.



Top Side Viewed from Top Bottom Side Viewed from Bottom







Wiring Patterns and connection diagram



www.gigalight.com

Optical Interconnection Design Innovator

		TABLE	VIRING	V				
	er housing)	P1(Extend			P1(Extender contact)			
	GND	01	\rightarrow	<	GND	01		
	TX2n	02	\rightarrow	←	TX2n	02		
	TX2p	03	\rightarrow	<	TX2p	03		
	GND	04	\rightarrow	<	GND	04		
	TX4n	05	\rightarrow	<	TX4n	05		
	TX4p	06	\rightarrow	<	TX4p	06		
	GND	07	\rightarrow	<	GND	07		
4# LEC	ModseIL	08	\longrightarrow	<	ModseIL	08		
5# LEC	ResetL	09	>	<	ResetL	09		
	SCL	11	\rightarrow	<	SCL	11		
	SDA	12	\rightarrow	<	SDA	12		
	GND	13	\rightarrow	<	GND	13		
	RX3p	14	\rightarrow	<	RX3p	14		
	RX3n	15	>	<	RX3n	15		
	GND	16	>	<	GND	16		
	RX1p	17	\rightarrow	<	RX1p	17		
1	RX1n	18		<	RX1n	18		
	GND	19	>	<	GND	19		
1	GND	20		<	GND	20		
	RX2n	21	\rightarrow	<	RX2n	21		
	RX2p	22		<	RX2p	22		
7	GND	23	>	<	GND	23		
1	RX2n	24		<	RX2n	24		
1	RX2p	25		<	RX2p	25		
1	GND	26	>		GND	26		
3# LEC	ModPrsL	27		− ←	ModPrsL	27		
4# LEC	IntL	28			IntL	28		
	VccTx	29		h	VccTx	29		
1# 2# L	Vccl	30		<	Vccl	30		
	VccRx	10	L	μ.	VccRx	10		
8# LEC	LPMode	31	~	<	LPMode	31		
-	GND	32	~	<	GND	32		
1	ТХЗр	33		<	ТХ3р	33		
1	TX3n	34		<	TX3n	34		
1	GND	35	~	<	GND	35		
1	TX1p	36		<	TX1p	36		
1	TX1n	37		<	TX1n	37		
7	GND	38		<	GND	38		

Figure 6. Wiring Patterns



Optical Interconnection Design Innovator

Extender housing pin and

parts



Figure 7. Extender housing pin and parts

Regulatory Compliance

Gigalight's 100GbE immersion cooling extender meet the requirements of the following standards:

Feature	Standard
Electrical Safety	EN 62368-1: 2014 IEC 62368-1:2014 UL 62368-1:2014
Environmental protection	Directive 2011/65/EU with amendment(EU)2015/863
CE EMC	EN55032: 2015 EN55035: 2017 EN61000-3-2:2014 EN61000-3-3:2013
FCC	FCC Part 15, Subpart B; ANSI C63.4-2014



Ordering information

Part Number	Length	Description
	10cm	100G QSFP28 extender with high speed cable, with nylon jacket ,
GLQE-PC101-D01	TUCITI	0.1meter length with connector and cage.
GLQE-PC101-D05	50cm	100G QSFP28 extender with high speed cable, with nylon jacket ,
		0.5meter length with connector and cage.

The length(meter) of GLQE-PC101-DXX is decimal and can be customizable.

Important Notice

Performance figures, data and any illustrative material provided in this data sheet are typical and must be specifically confirmed in writing by GIGALIGHT before they become applicable to any particular order or contract. In accordance with the GIGALIGHT policy of continuous improvement specifications may change without notice.

The publication of information in this data sheet does not imply freedom from patent or other protective rights of GIGALIGHT or others. Further details are available from any GIGALIGHT sales representative.

sales@gigalight.com.cn http://www.gigalight.com

Revision History

Revision	Date	Description
V0	22-Apr-2023	Advance Release.